



PRO-VIDEO-SW2-60 (G3) Additional camera switch

Additional camera switch module in PRO system. Enables connecting up to 4 additional cameras. Each switch supports one additional camera. The cameras can be operated globally by all monitors or individually for each monitor address as long as the sum of all supported cameras in the system is less than or equal to 4. Switching the image from the individual cameras is done with the "monitor" icon/button. Designed for mounting in an electrical box Ø60mm. Compatible with all COMO/ Familio PRO, PRO-A devices. The module is also required when connecting two panels of the COMO-PRO Master and Slave (it is used to switch the camera images of individual panels). This is the next generation of the module (G3), which supports, among other things, a larger number of addresses (e.g. for GLASS-PRO-7 series monitors), and also enables programming of settings and software update on the system bus using a computer. Reliability, innovation and durability are the hallmarks of the ACO brand.

Index	PRO-VIDEO-SW2-60 (G3)
Description	Additional camera switch module for an installation box Φ 60mm
Dimensions (mm)	50x50x18
Design	PCV foam casing (bottom side)
Installation type	Digital PRO system: twisted pair cat. 5e or 6
Power supply	15VDC / 26mA
Power consumption in standby mode	~0,3W
Outputs	5 x screw terminals (PRO system bus connection): - audio signal connection: "LINE" - power connection: "+DC" and "-DC" - connecting the video signal: "V+" and "V-"
Inputs	5 x screw terminals (PRO system bus connection): - audio signal connection: "LINE" - power connection: "+DC" and "-DC" - connecting the video signal: "V+" and "V-" 5 x screw connections - to connect the audio signal: "LINE" - power connection: "+DC" and "-DC" - connecting an external video signal from an additional camera: "V+" and "V-" (differential signal)
Attributes	<ul style="list-style-type: none"> - possibility of connecting an additional camera in the PRO system - more switches can be used to connect up to 4 additional cameras in the system - up to 4 switches can be connected to all monitors in the system, which are supported globally - Up to 4 switches can be connected for each address individually (only operated by a monitor with the same address) - addressing the module in the same way as PRO system receivers - supports the addresses of the receivers: 31 addresses (programmed with

- switches on the module) or 1023 addresses (programmed from a computer using the optional PRO-USB interface)
- for address 0 the module is supported by all receivers in the system
 - the monitors detect the number of switches connected
 - compatible with the entire PRO system
 - is located in an installation box with a diameter of 60mm
 - module supported by monitors from software version: v1.3 for MPRO7; v1.6 for MPRO; GLASS-PRO (regardless of version)
 - the module works as a switch for cameras in COMO series panels when two Master/Slave panels are in operation
- Other functions related to the 3rd generation of the module:
- programming of settings and software update on the system bus (PRO-USB computer interface required)
 - compatible with previous generations of the PRO system
 - the individual number of each device: DevID
 - searching for all devices in the system
 - individual or group management of equipment
 - possibility to manage devices and updates in a working system
 - one software to handle all devices: PRO 3 Manager